



Original Bushing Information

Original Bushing Manufacturer: G.E. **Mounting Position:**
Catalog Number: 11B905
Voltage Class (kV): 362 **BIL (kV):** 1050

Application	DrawLead	Bottom Connected	Oil Circuit Breaker
Current Rating (Amps)	800		
362X0800UB (Amps)	800		

General Comments:

Replacement Information

ABB Style Number: [362X0800UB](#) **Alternate ABB Style Number:**

Review dimensional differences verifying critical dimensions to meet application requirements.

Notes/Comments: (A) ABB bushing is 1300 kV BIL (B) Draw lead cable adapter required. Remove old connector and braze adapter to end of cable. (C) New line terminal required.

Catalog Number	BIL	EL	CT	L	B	D	Bolt Circle	No. Of Holes	Hole Dia. (inches)	Creep
11B905	1050kV	23 in.	23 in.	51 in.	132 in.	15.75 in.	21 in.	12	1.250 slots in.	257.6 in.
362X0800UB	1300kV	23 in.	23 in.	51.031 in.	132.656 in.	15.75 in.	21 in.	12	1.25 in.	262.125 in.

Catalog Number	Strike	P Dia.	Cable Height/Pin Height for AB Bushing - CH	LHV	Top Terminal Threads (inches)	Bottom Terminal Thread/Configuration
11B905	102 in.	16.88 in.	120.44 in.	108 in.	2.0-12x2.5	2" TUBE ID
362X0800UB	101.984 in.	16.875 in.	129.267 in.	107.984 in.	1.500-12x2.0 x 12 UN-2A	2.0 id tube 2.000 in.I.D. Tube

Cable Adapter: P492B596P24

Flange Adapter: NONE