



Original Bushing Information

Original Bushing Manufacturer: G.E. **Mounting Position:**
Catalog Number: 11B579
Voltage Class (kV): 115 **BIL (kV):** 550

Application	DrawLead	Bottom Connected	Oil Circuit Breaker
Current Rating (Amps)		1600	
115W2000DJ (Amps)		2000	

General Comments:

Replacement Information

ABB Style Number: [115W2000DJ](#) **Alternate ABB Style Number:**

Review dimensional differences verifying critical dimensions to meet application requirements.

Notes/Comments:

Catalog Number	BIL	EL	CT	L	B	D	Bolt Circle	No. Of Holes	Hole Dia. (inches)	Creep
11B579	550kV	23 in.	23 in.	43 in.	64.625 in.	8.75 in.	13.25 in.		1.25 in.	114 in.
115W2000DJ	550kV	23 in.	23 in.	42.984 in.	68.125 in.	8.75 in.	13.25 in.	6	1.25 in.	125.188 in.

Catalog Number	Strike	P Dia.	Cable Height/Pin Height for AB Bushing - CH	LHV	Top Terminal Threads (inches)	Bottom Terminal Thread/Configuration
11B579	50.875 in.	9.625 in.	N/A	56.875 in.	2"-12 X 2.5" LG SIL PLT	ANSI FIG # 2
115W2000DJ	50.891 in.	9.625 in.	N/A	56.891 in.	2.0-12x3.250 SP x	(4) .375-16 x 3.75 B.C./(8) .500-13UN x 6.75 B.C. N/A

Cable Adapter:

NONE

Flange Adapter:

NONE