



Original Bushing Information

Original Bushing Manufacturer: G.E. **Mounting Position:** Vertical

Catalog Number: 11B592BB

Voltage Class (kV): 115 **BIL (kV):** 550

Application	DrawLead	Bottom Connected	Oil Circuit Breaker
Current Rating (Amps)	800		
115W0800XA (Amps)	800		

General Comments:

Replacement Information

ABB Style Number: [115W0800XA](#) **Alternate ABB Style Number:**

Review dimensional differences verifying critical dimensions to meet application requirements.

Notes/Comments:

Catalog Number	BIL	EL	CT	L	B	D	Bolt Circle	No. Of Holes	Hole Dia. (inches)	Creep
11B592BB	550kV	23 in.	23 in.	43.438 in.	57.938 in.	8.75 in.	13.25 in.	6	1.25 in.	N/A
115W0800XA	550kV	23 in.	23 in.	43.422 in.	57.812 in.	8.75 in.	13.25 in.	6	1.25 in.	104.5 in.

Catalog Number	Strike	P Dia.	Cable Height/Pin Height for AB Bushing - CH	LHV	Top Terminal Threads (inches)	Bottom Terminal Thread/Configuration
11B592BB	35.188 in.	9.625 in.	47.81 in.	41.19 in.	1.500-12x2.0	1.625 id tube
115W0800XA	42.14 in.	9.625 in.	47.733 in.	48.14 in.	1.500-12UN-2A, 2.125 USABLE THD, SP x 12 UN-2A	1.625 id tube 1.625 in.I.D. Tube

Cable Adapter:

NONE

Flange Adapter:

NONE