



Original Bushing Information

Original Bushing Manufacturer: G.E. **Mounting Position:** Vertical

Catalog Number: 11B631BB

Voltage Class (kV): 138 **BIL (kV):** 650

Application	DrawLead	Bottom Connected	Oil Circuit Breaker
Current Rating (Amps)	800		
138W0800AA (Amps)	800		

General Comments: For 800 amp draw lead application only.

Replacement Information

ABB Style Number: [138W0800AA](#) **Alternate ABB Style Number:**

Review dimensional differences verifying critical dimensions to meet application requirements.

Notes/Comments:

Catalog Number	BIL	EL	CT	L	B	D	Bolt Circle	No. Of Holes	Hole Dia. (inches)	Creep
11B631BB	650kV	23 in.	23 in.	47.18 in.	58.25 in.	9.75 in.	14.25 in.	6	1.25 slots in.	N/A
138W0800AA	650kV	23 in.	23 in.	47.172 in.	57.813 in.	9.75 in.	14.25 in.	6	1.25 in.	104.188 in.

Catalog Number	Strike	P Dia.	Cable Height/Pin Height for AB Bushing - CH	LHV	Top Terminal Threads (inches)	Bottom Terminal Thread/Configuration
11B631BB	42.125 in.	10.625 in.	48.13 in.	N/A	1.5-12x2.0, SP	1.625 id tube
138W0800AA	42.141 in.	9.500 in.	47.734 in.	48.141 in.	1.500-12UN-2A, 2.125 USABLE THD, SP x 12 UN-2A	1.625 id tube 1.625 in. Hollow Tube