



Original Bushing Information

Original Bushing Manufacturer: G.E. **Mounting Position:**
Catalog Number: 11B640BB
Voltage Class (kV): 138 **BIL (kV):** 650

Application	DrawLead	Bottom Connected	Oil Circuit Breaker
Current Rating (Amps)		3000	
138W3000UQ (Amps)		3000	

General Comments:

Replacement Information

ABB Style Number: [138W3000UQ](#) **Alternate ABB Style Number:**

Review dimensional differences verifying critical dimensions to meet application requirements.

Notes/Comments:

Catalog Number	BIL	EL	CT	L	B	D	Bolt Circle	No. Of Holes	Hole Dia. (inches)	Creep
11B640BB	650kV	23 in.	23 in.	46.69 in.	58.32 in.	10.75 in.	15.75 in.	8	1.25 slots in.	100.5 in.
138W3000UQ	650kV	23 in.	23 in.	46.671 in.	58.048 in.	10.75 in.	15.75 in.	8	1.25 in.	100.5 in.

Catalog Number	Strike	P Dia.	Cable Height/Pin Height for AB Bushing - CH	LHV	Top Terminal Threads (inches)	Bottom Terminal Thread/Configuration
11B640BB	42.63 in.	N/A	N/A	48.63 in.	3.0-12 X 3.0	ansi/IEEE fig 3
138W3000UQ	42.641 in.	11.375 in.	N/A	48.641 in.	3.0-12x3.750 x	IEEE fig 3 N/A

Cable Adapter:

NONE

Flange Adapter:

NONE