



**Original Bushing Information**

Original Bushing Manufacturer: G.E.      Mounting Position: Vertical  
 Catalog Number: 11B642BB  
 Voltage Class (kV): 138      BIL (kV): 650

Application	DrawLead	Bottom Connected	Oil Circuit Breaker
Current Rating (Amps)		3000	
138W3000UQ (Amps)		3000	

**General Comments:**

**Replacement Information**

ABB Style Number: [138W3000UQ](#) Alternate ABB Style Number: [138W3000UT](#)

**Review dimensional differences verifying critical dimensions to meet application requirements.**

**Notes/Comments:** Note Differences In "B" and "Strike" - Confirm if acceptable.

Catalog Number	BIL	EL	CT	L	B	D	Bolt Circle	No. Of Holes	Hole Dia. (inches)	Creep
11B642BB	650kV	23 in.	23 in.	46.688 in.	68.375 in.	10.5 in.	15.75 in.	8	1.25 in.	N/A
138W3000UQ	650kV	23 in.	23 in.	46.671 in.	58.048 in.	10.75 in.	15.75 in.	8	1.25 in.	100.5 in.

Catalog Number	Strike	P Dia.	Cable Height/Pin Height for AB Bushing - CH	LHV	Top Terminal Threads (inches)	Bottom Terminal Thread/Configuration
11B642BB	51.375 in.	12.125 in.	N/A	N/A	3-12 x 3.125 SP	(8) .500-13 Holes on 6.75" BC
138W3000UQ	42.641 in.	11.375 in.	N/A	48.641 in.	3.0-12x3.750 x	IEEE fig 3 N/A

**Cable Adapter:** NONE

**Flange Adapter:** NONE