



Original Bushing Information

Original Bushing Manufacturer: G.E. **Mounting Position:**
Catalog Number: 11B671
Voltage Class (kV): 362 **BIL (kV):** 1050

Application	DrawLead	Bottom Connected	Oil Circuit Breaker
Current Rating (Amps)		2000	
362W2000WY (Amps)		2000	

General Comments:

Replacement Information

ABB Style Number: [362W2000WY](#) **Alternate ABB Style Number:**

Review dimensional differences verifying critical dimensions to meet application requirements.

Notes/Comments:

Catalog Number	BIL	EL	CT	L	B	D	Bolt Circle	No. Of Holes	Hole Dia. (inches)	Creep
11B671	1050kV	23 in.	23 in.	59.875 in.	127.688 in.	14.88 in.	21 in.	12	1.25 in.	N/A
362W2000WY	1050kV	23 in.	23 in.	59.813 in.	127.969 in.	14.875 in.	21 in.	12	1.25 in.	264.75 in.

Catalog Number	Strike	P Dia.	Cable Height/Pin Height for AB Bushing - CH	LHV	Top Terminal Threads (inches)	Bottom Terminal Thread/Configuration
11B671	101.938 in.	16.875 in.	N/A	107.938 in.	2"-12 x 2.625	(8) .5-13 holes 6.75 bc
362W2000WY	101.969 in.	16.875 in.	N/A	107.969 in.	2.0-12x3.062, SP x	(8).5-13holes X 0.750 DEEP 6.75 bc N/A

Cable Adapter:

NONE

Flange Adapter:

NONE