



**Original Bushing Information**

**Original Bushing Manufacturer:** G.E.    **Mounting Position:**  
**Catalog Number:** 11B722  
**Voltage Class (kV):** 180    **BIL (kV):** 825

Application	DrawLead	Bottom Connected	Oil Circuit Breaker
Current Rating (Amps)	800		
196W0800XA (Amps)	800		

**General Comments:**

**Replacement Information**

**ABB Style Number:** [196W0800XA](#)    **Alternate ABB Style Number:**

**Review dimensional differences verifying critical dimensions to meet application requirements.**

**Notes/Comments:** Note Difference in Tube ID. Confirm if acceptable.

Catalog Number	BIL	EL	CT	L	B	D	Bolt Circle	No. Of Holes	Hole Dia. (inches)	Creep
11B722	825kV	26.75 in.	26.75 in.	57.25 in.	104.625 in.	12.375 in.	21 in.	12	1.25 in.	N/A
196W0800XA	900kV	26.75 in.	26.75 in.	60.046 in.	91.422 in.	12 in.	21 in.	12	1.25 in.	178 in.

Catalog Number	Strike	P Dia.	Cable Height/Pin Height for AB Bushing - CH	LHV	Top Terminal Threads (inches)	Bottom Terminal Thread/Configuration
11B722	74.688 in.	16.875 in.	91.875 in.	60.687 in.	1.50-12x2.125, SP	2.25 id tube
196W0800XA	64.593 in.	16.875 in.	81.33 in.	70.593 in.	1.50-12x2.0, SP x 12 UN-2A	2.0 id tube 2.000 in.I.D. Tube

**Cable Adapter:** NONE  
**Flange Adapter:** NONE