



Original Bushing Information

Original Bushing Manufacturer: G.E. Mounting Position:
 Catalog Number: 11B766
 Voltage Class (kV): 362 BIL (kV): 1175

Application	DrawLead	Bottom Connected	Oil Circuit Breaker
Current Rating (Amps)	800		
362W0800VF (Amps)	800		

General Comments:

Replacement Information

ABB Style Number: [362W0800VF](#) Alternate ABB Style Number:

Review dimensional differences verifying critical dimensions to meet application requirements.

Notes/Comments: Note: Cable Adapter Required. Note Difference in "B" - External Buss May Need Adjusted

Catalog Number	BIL	EL	CT	L	B	D	Bolt Circle	No. Of Holes	Hole Dia. (inches)	Creep
11B766	1175kV	23 in.	23 in.	63.12 in.	130.63 in.	15.12 in.	21 in.	12	1.250 in.	N/A
362W0800VF	1175kV	23 in.	23 in.	63.063 in.	132.406 in.	15.125 in.	21 in.	12	1.25 in.	262.125 in.

Catalog Number	Strike	P Dia.	Cable Height/Pin Height for AB Bushing - CH	LHV	Top Terminal Threads (inches)	Bottom Terminal Thread/Configuration
11B766	101.9 in.	16.875 in.	120.38 in.	108 in.	1.5-12x2.12	(8) .50-13holes 6.75 bc 2.25 ID TUBE
362W0800VF	101.969 in.	16.875 in.	125.923 in.	107.968 in.	1.500-12UN-2A 2.125 USABLE x	(8) .50-13holes 6.75 bc 2.00 ID TUBE N/A

Cable Adapter: 1ZUA264308-BAA

Flange Adapter: NONE