



Original Bushing Information

Original Bushing Manufacturer: G.E. **Mounting Position:**
Catalog Number: 11B877BB
Voltage Class (kV): 362 **BIL (kV):** 1050

Application	DrawLead	Bottom Connected	Oil Circuit Breaker
Current Rating (Amps)		1600	
362W2000UZ (Amps)		2000	

General Comments:

Replacement Information

ABB Style Number: [362W2000UZ](#) **Alternate ABB Style Number:**

Review dimensional differences verifying critical dimensions to meet application requirements.

Notes/Comments:

Catalog Number	BIL	EL	CT	L	B	D	Bolt Circle	No. Of Holes	Hole Dia. (inches)	Creep
11B877BB	1050kV	23 in.	23 in.	51 in.	128.19 in.	15.75 in.	21 in.	12	1.25 slots in.	257.6 in.
362W2000UZ	1300kV	23 in.	23 in.	51.031 in.	128.172 in.	15.75 in.	21 in.	12	1.25 in.	262.125 in.

Catalog Number	Strike	P Dia.	Cable Height/Pin Height for AB Bushing - CH	LHV	Top Terminal Threads (inches)	Bottom Terminal Thread/Configuration
11B877BB	102 in.	16.875 in.	N/A	108 in.	2-12x2.5	IEEE table 7
362W2000UZ	101.984 in.	16.875 in.	N/A	107.984 in.	2.00-12x2.5, SP x	(8).5-13holes x .750 Deep 6.75 bc N/A

Cable Adapter:

NONE

Flange Adapter:

NONE