



Original Bushing Information

Original Bushing Manufacturer: G.E. **Mounting Position:**
Catalog Number: 11B905BB
Voltage Class (kV): 362 **BIL (kV):** 1050

Application	DrawLead	Bottom Connected	Oil Circuit Breaker
Current Rating (Amps)	800		
362W0800UB (Amps)	800		

General Comments:

Replacement Information

ABB Style Number: [362W0800UB](#) **Alternate ABB Style Number:**

Review dimensional differences verifying critical dimensions to meet application requirements.

Notes/Comments: (A) ABB bushing is 1300 kV BIL (B) Cable adapter is required. (C) New line terminal required.

Catalog Number	BIL	EL	CT	L	B	D	Bolt Circle	No. Of Holes	Hole Dia. (inches)	Creep
11B905BB	1050kV	23 in.	23 in.	51 in.	132 in.	15.75 in.	21 in.	12	1.250 slots in.	257.6 in.
362W0800UB	1300kV	23 in.	23 in.	51.031 in.	132.656 in.	15.75 in.	21 in.	12	1.25 in.	262.125 in.

Catalog Number	Strike	P Dia.	Cable Height/Pin Height for AB Bushing - CH	LHV	Top Terminal Threads (inches)	Bottom Terminal Thread/Configuration
11B905BB	102 in.	16.88 in.	120.44 in.	108 in.	2.0-12x2.5	2" TUBE ID
362W0800UB	101.984 in.	16.875 in.	126.219 in.	107.984 in.	1.500-12x2.0 x 12 UN-2A	2.0 id tube 2.000 in.I.D. Tube

Cable Adapter: 1ZUA264308-BAA

Flange Adapter: NONE