



Original Bushing Information

Original Bushing Manufacturer: G.E. **Mounting Position:**
Catalog Number: 11B910BB
Voltage Class (kV): 138 **BIL (kV):** 650

Application	DrawLead	Bottom Connected	Oil Circuit Breaker
Current Rating (Amps)		4000	
138W4000XR (Amps)		4000	

General Comments:

Replacement Information

ABB Style Number: [138W4000XR](#) **Alternate ABB Style Number:**

Review dimensional differences verifying critical dimensions to meet application requirements.

Notes/Comments:

Catalog Number	BIL	EL	CT	L	B	D	Bolt Circle	No. Of Holes	Hole Dia. (inches)	Creep
11B910BB	650kV	23 in.	23 in.	46.75 in.	68.31 in.	12 in.	15.75 in.	8	1.250 in.	N/A
138W4000XR	650kV	23 in.	23 in.	46.781 in.	74.047 in.	12 in.	15.75 in.	8	1.25 in.	137 in.

Catalog Number	Strike	P Dia.	Cable Height/Pin Height for AB Bushing - CH	LHV	Top Terminal Threads (inches)	Bottom Terminal Thread/Configuration
11B910BB	44.06 in.	12.375 in.	NA in.	49.06 in.	4-10x4.5	ansi/IEEE fig 3
138W4000XR	49.984 in.	12.375 in.	N/A	55.984 in.	4.0-10 x 4.375 x	(8) .500-13UN-2B tapped holes on a 6.75 dia BC N/A

Cable Adapter:

NONE

Flange Adapter:

NONE