



Original Bushing Information

Original Bushing Manufacturer: G.E. **Mounting Position:**
Catalog Number: 11B989BB
Voltage Class (kV): 550 **BIL (kV):** 1550

Application	DrawLead	Bottom Connected	Oil Circuit Breaker
Current Rating (Amps)		3000	
550W3000BF (Amps)		3000	

General Comments:

Replacement Information

ABB Style Number: [550W3000BF](#) **Alternate ABB Style Number:**

Review dimensional differences verifying critical dimensions to meet application requirements.

Notes/Comments:

Catalog Number	BIL	EL	CT	L	B	D	Bolt Circle	No. Of Holes	Hole Dia. (inches)	Creep
11B989BB	1550kV	27 in.	27 in.	65 in.	191.25 in.	20 in.	25 in.	12	1.250 in.	N/A
550W3000BF	1550kV	27 in.	27 in.	65 in.	190.938 in.	20 in.	25 in.	12	1.25 in.	362.5 in.

Catalog Number	Strike	P Dia.	Cable Height/Pin Height for AB Bushing - CH	LHV	Top Terminal Threads (inches)	Bottom Terminal Thread/Configuration
11B989BB	153.3 in.	N/A	NA in.	160.3 in.	3-12x3.13	ansi fig 3
550W3000BF	153.312 in.	20.75 in.	N/A	160.313 in.	3.0-12x2.5 x 12 UN-2A	(8) .50-13 x .938 deep on 6.75 BC (8) .500-13 in.

Cable Adapter:

NONE

Flange Adapter:

NONE