



Original Bushing Information

Original Bushing Manufacturer: G.E. **Mounting Position:**
Catalog Number: 17B039BB
Voltage Class (kV): 34 **BIL (kV):** 200

Application	DrawLead	Bottom Connected	Oil Circuit Breaker
Current Rating (Amps)		5000	
034W5000UW (Amps)		5000	

General Comments:

Replacement Information

ABB Style Number: [034W5000UW](#) **Alternate ABB Style Number:**

Review dimensional differences verifying critical dimensions to meet application requirements.

Notes/Comments:

Catalog Number	BIL	EL	CT	L	B	D	Bolt Circle	No. Of Holes	Hole Dia. (inches)	Creep
17B039BB	200kV	10 in.	10 in.	25.75 in.	42.13 in.	8.5 in.	14.25 in.	6	1.25 slots in.	49.5 in.
034W5000UW	200kV	10 in.	10 in.	25.75 in.	42.125 in.	8.5 in.	14.25 in.	6	1.25 in.	49.5 in.

Catalog Number	Strike	P Dia.	Cable Height/Pin Height for AB Bushing - CH	LHV	Top Terminal Threads (inches)	Bottom Terminal Thread/Configuration
17B039BB	24.5 in.	9.63 in.	N/A	30.5 in.	4.0-12 x 5.875	(4) hole spade, 1.75 c-c
034W5000UW	24.5 in.	9.625 in.	N/A	30.5 in.	4.0-10x5.875 x	(4) .562 hole blade N/A

Cable Adapter:

NONE

Flange Adapter:

NONE