



**Original Bushing Information**

**Original Bushing Manufacturer:** G.E.      **Mounting Position:**  
**Catalog Number:** 17B067BB  
**Voltage Class (kV):** 69      **BIL (kV):** 350

Application	DrawLead	Bottom Connected	Oil Circuit Breaker
Current Rating (Amps)		3000	
069W3000UJ (Amps)		3000	

**General Comments:**

**Replacement Information**

**ABB Style Number:** [069W3000UJ](#) **Alternate ABB Style Number:**

**Review dimensional differences verifying critical dimensions to meet application requirements.**

**Notes/Comments:**

Catalog Number	BIL	EL	CT	L	B	D	Bolt Circle	No. Of Holes	Hole Dia. (inches)	Creep
17B067BB	350kV	19 in.	19 in.	32.94 in.	41.44 in.	7.5 in.	10.88 in.	6	.75 holes in.	58.5 in.
069W3000UJ	350kV	19 in.	19 in.	32.938 in.	42.367 in.	6.875 in.	10.875 in.	6	0.75 in.	97.565 in.

Catalog Number	Strike	P Dia.	Cable Height/Pin Height for AB Bushing - CH	LHV	Top Terminal Threads (inches)	Bottom Terminal Thread/Configuration
17B067BB	30.44 in.	7.5 in.	in.	33.4 in.	3-12X3.12	2.81X3.56 BEVEL 0.375-16 TAP (8) ON 6in B.C.
069W3000UJ	32.867 in.	6.5 in.	N/A	34.742 in.	3.0-12x3.625 USABLE, SP x	(8) .375-16UN on 6.0 bc, .875 deep N/A

**Cable Adapter:**

NONE

**Flange Adapter:**

NONE