



Original Bushing Information

Original Bushing Manufacturer: G.E. **Mounting Position:**
Catalog Number: 17B602BB
Voltage Class (kV): 69 **BIL (kV):** 350

Application	DrawLead	Bottom Connected	Oil Circuit Breaker
Current Rating (Amps)	400	1200	
069W0412XN (Amps)	400	1200	1200

General Comments:

Replacement Information

ABB Style Number: 069W0412XN **Alternate ABB Style Number:**

Review dimensional differences verifying critical dimensions to meet application requirements.

Notes/Comments:

Catalog Number	BIL	EL	CT	L	B	D	Bolt Circle	No. Of Holes	Hole Dia. (inches)	Creep
17B602BB	350kV	21 in.	21 in.	37.5 in.	41.17 in.	5.25 in.	9.25 in.	6	0.875 slots in.	72 in.
069W0412XN	350kV	21 in.	21 in.	37.437 in.	41.172 in.	5.15 in.	9.25 in.	6	0.875 in.	70.406 in.

Catalog Number	Strike	P Dia.	Cable Height/Pin Height for AB Bushing - CH	LHV	Top Terminal Threads (inches)	Bottom Terminal Thread/Configuration
17B602BB	27.38 in.	5.75 in.	36.63 in.	30.38 in.	1.5-12x2.125	1.5-12x2.25, .875 tube ID
069W0412XN	27.375 in.	5.75 in.	36.75 in.	39.422 in.	1.5-12X2.25 x 12 UN-2A	1.5-12x2.25, .875 id tube 1.500 in.12 UN-2A

Cable Adapter:

NONE

Flange Adapter:

NONE