



Original Bushing Information

Original Bushing Manufacturer: G.E. **Mounting Position:**
Catalog Number: 1B565
Voltage Class (kV): 25 **BIL (kV):** 150

Application	DrawLead	Bottom Connected	Oil Circuit Breaker
Current Rating (Amps)		6000	
025J0600BN (Amps)		6000	

General Comments:

Replacement Information

ABB Style Number: [025J0600BN](#) **Alternate ABB Style Number:**

Review dimensional differences verifying critical dimensions to meet application requirements.

Notes/Comments:

Catalog Number	BIL	EL	CT	L	B	D	Bolt Circle	No. Of Holes	Hole Dia. (inches)	Creep
1B565	150kV	21 in.	21 in.	34.56 in.	20.88 in.	8.13 in.	14.25 in.	6	.875 holes in.	32 in.
025J0600BN	150kV	21 in.	21 in.	34.609 in.	20.829 in.	8.111 in.	14.25 in.	6	0.875 in.	32 in.

Catalog Number	Strike	P Dia.	Cable Height/Pin Height for AB Bushing - CH	LHV	Top Terminal Threads (inches)	Bottom Terminal Thread/Configuration
1B565	12.44 in.	8.44 in.	N/A	16.25 in.	4- (6) hole spades, .688 holes	1- (4) hole spade, .688 holes
025J0600BN	12.422 in.	8.438 in.	N/A	16.141 in.	(6) .688 holes per blade, (4) blades x	(4) .688 hole blade N/A

Cable Adapter:

NONE

Flange Adapter:

NONE