



Original Bushing Information

Original Bushing Manufacturer: G.E. **Mounting Position:**
Catalog Number: 1B566
Voltage Class (kV): 25 **BIL (kV):** 150

Application	DrawLead	Bottom Connected	Oil Circuit Breaker
Current Rating (Amps)		7500	
025J0750BK (Amps)		7500	

General Comments:

Replacement Information

ABB Style Number: 025J0750BK **Alternate ABB Style Number:**

Review dimensional differences verifying critical dimensions to meet application requirements.

Notes/Comments:

Catalog Number	BIL	EL	CT	L	B	D	Bolt Circle	No. Of Holes	Hole Dia. (inches)	Creep
1B566	150kV	N/A	N/A	15.62 in.	18.75 in.	8.13 in.	14.25 in.	6	.875 holes in.	21.31 in.
025J0750BK	150kV	0 in.	0 in.	16.625 in.	18.688 in.	8.111 in.	14.25 in.	6	0.875 in.	21.312 in.

Catalog Number	Strike	P Dia.	Cable Height/Pin Height for AB Bushing - CH	LHV	Top Terminal Threads (inches)	Bottom Terminal Thread/Configuration
1B566	10.31 in.	8.44 in.	N/A	14.06 in.	(6) .688 holes per blade, (4) blades	(6) .688 holes per blade, (1) blade
025J0750BK	10.312 in.	8.438 in.	N/A	14 in.	(6) .688 holes per blade, (4) blades, SP x	(6) .688 holes per blade, (1) blade N/A

Cable Adapter:

NONE

Flange Adapter:

NONE