



**Original Bushing Information**

**Original Bushing Manufacturer:** G.E. **Mounting Position:**  
**Catalog Number:** 1B571  
**Voltage Class (kV):** 25 **BIL (kV):** 150

Application	DrawLead	Bottom Connected	Oil Circuit Breaker
Current Rating (Amps)		12000	
025K1200BB (Amps)		12000	

**General Comments:**

**Replacement Information**

**ABB Style Number:** 025K1200BB **Alternate ABB Style Number:**

**Review dimensional differences verifying critical dimensions to meet application requirements.**

**Notes/Comments:**

Catalog Number	BIL	EL	CT	L	B	D	Bolt Circle	No. Of Holes	Hole Dia. (inches)	Creep
1B571	150kV	27 in.	27 in.	44.5 in.	20.75 in.	14.2 in.	21 in.	12	.875 holes in.	33 in.
025K1200BB	150kV	27 in.	27 in.	44.578 in.	20.672 in.	14.163 in.	21 in.	12	0.875 in.	32 in.

Catalog Number	Strike	P Dia.	Cable Height/Pin Height for AB Bushing - CH	LHV	Top Terminal Threads (inches)	Bottom Terminal Thread/Configuration
1B571	12.44 in.	14.32 in.	N/A	15.94 in.	4- (10) hole spades, .688 holes	2- (6) hole spades, .688 holes
025K1200BB	12.421 in.	14.625 in.	N/A	15.859 in.	(10) .688h/b(4)b x	(6) .688 h/b (2)b N/A

**Cable Adapter:**

NONE

**Flange Adapter:**

NONE