



**Original Bushing Information**

**Original Bushing Manufacturer:** G.E.      **Mounting Position:**  
**Catalog Number:** 1B638BB  
**Voltage Class (kV):** 25      **BIL (kV):** 150

Application	DrawLead	Bottom Connected	Oil Circuit Breaker
Current Rating (Amps)		600	
025J0060AE (Amps)	600		

**General Comments:**

**Replacement Information**

**ABB Style Number:** 025J0060AE **Alternate ABB Style Number:**

**Review dimensional differences verifying critical dimensions to meet application requirements.**

**Notes/Comments:**

Catalog Number	BIL	EL	CT	L	B	D	Bolt Circle	No. Of Holes	Hole Dia. (inches)	Creep
1B638BB	150kV	0 in.	N/A	8.38 in.	14 in.	3 in.	6 in.	4	0.630 in.	20.7 in.
025J0060AE	150kV	N/A	N/A	8.375 in.	14 in.	3 in.	6 in.	4	0.625 in.	20.7 in.

Catalog Number	Strike	P Dia.	Cable Height/Pin Height for AB Bushing - CH	LHV	Top Terminal Threads (inches)	Bottom Terminal Thread/Configuration
1B638BB	9.31 in.	N/A	9.38 in.	10.75 in.	1.12-12x2.0	1.562 min ID
025J0060AE	9.312 in.	3.250 in.	4.625 in.	10.75 in.	1.125-12x2.0 x 12 UN-2A	1.562 i.d. porcelain 1.562 in.I.D. Tube

**Cable Adapter:**

NONE

**Flange Adapter:**

NONE